

SANGEAN

World Receiver (ProTravel)			
MODEL		PT-50	
TUNING		Type	Analogue
		Rotary Tuning	V
DISPLAY		Type	LCD
		Size (inch)	1.4" x 1.14"
		Back light	V
BAND	FM	Frequency (MHz)	87.5 - 108
		Stereo (Via Headphone)	V
	MW	Frequency (kHz)	530 - 1710
	SW	Frequency (MHz)	SW1 - 7
		Meter bands	49,41,31,25,
			22,19,16,
CLOCK		Real time	V
		Dual / World time	World time
		Alarm Radio	V
		Alarm Buzzer	HWS
		Snooze	V
		Sleep	V
OUTPUT DEVICES		Speaker unit	2 inches 4 ohm
OUTPUT POWER (TYPICAL)		Batteries (Speaker)	100 mW
		Earphones	5 + 5 mW
POWER SUPPLY		DC in	3 - 6V DC 300 mA
		Batteries (Main power)	2 x 1.5V (UM-3)
I/O SOCKET		DC in	V
		Earphones	V
ACCESSORIES		Carrying pouch	V
DIMENSIONS		Width (inch)	5 1/5
		Height (inch)	3 1/2
		Depth (inch)	1 1/3
		Weight (lb. oz)	9.67 oz