

# SANGEAN

Utility Radio		
MODEL		U3
TUNING	Type	PLL synthesized
	Memory Presets	FM x 5 / AM x 5
	Rotary Tuning	V
	Auto Tuning System	V
DISPLAY	Type	LCD (TN)
	Size ( mm )	99.6 x 24.6
	Back light	V
BAND	FM	Frequency ( MHz ) 87.5 - 108
	LW	Frequency ( kHz ) 153 - 279 ( Option )
	MW	Frequency ( kHz ) 520 - 1710
CLOCK	Real time clock	V
	Alarm Radio	V
	Alarm Buzzer	HWS
	Snooze	V
	Sleep	V
AUDIO TONE	Tone control	V ( Rotary )
	Deep bass compensation	V
OUTPUT DEVICES	Speaker unit	6.5 inches 8 ohm
OUTPUT POWER ( TYPICAL )	AC / DC in ( Speaker )	7W ( AC / DC )
	Batteries ( Speaker )	4.5W
	Earphones	5 + 5 mW ( monaural )
POWER SUPPLY	AC - USA	120V 60 Hz
	AC - EUR	230V 50 Hz
	DC in	9 - 14V DC 1A
	Batteries ( Main power )	6 x 1.5V ( UM - 1 )
I/O SOCKET	DC in	V
	Earphones	V
	AUX in	V
	DC output	5V 500mA
SPECIAL PERFORMANCE	Water resistance	JIS - 4
	LED illuminator	V
DIMENSIONS	Width ( inch )	10.2
	Height ( inch )	14.6
	Depth ( inch )	9.8
	Weight ( lb. oz )	9lb. 5.7oz